

HT-4612E JUMPER SETTING

- **JP1 : CMOS DATA CONTROL**
 - Pin 1-2 Short : Clear CMOS
 - Pin 2-3 Short : Normal**

- **JP4 : PS2 MOUSE LOOP BACK**
 - All Open : Through PS/2 Touch Controller
 - Pin 1-2 Short 、 Pin 3-4 Short : No PS/2 Touch Controller**

- **JP6 : COM2/COM3 DC SUPPLY SELECT**
 - Pin 1-3 Short : COM3 support 12V function
 - Pin 3-5 Short : COM3 Pin1 connected as DCD**
 - Pin 2-4 Short : COM2 support 12V function
 - Pin 4-6 Short : COM2 Pin1 connected as DCD**

- **JP7 : MICRO Processor Firmware Update Header**

- **JP9 : COM1/COM4 DC SUPPLY SELECT**
 - Pin 1-3 Short : COM1 support 12V function
 - Pin 3-5 Short : COM1 Pin1 connected as DCD**
 - Pin 2-4 Short : COM4 support 12V function
 - Pin 4-6 Short : COM4 Pin1 connected as DCD**

- **JP10 : COM1/COM4 DC SUPPLY SELECT**
 - Pin 1-3 Short : COM1 support 5V function
 - Pin 3-5 Short : COM1 Pin9 connected as RI**
 - Pin 2-4 Short : COM4 support 5V function
 - Pin 4-6 Short : COM4 Pin9 connected as RI**

